

# RE - XP Series PA Expander



## Product Overview

RE-XP Series Expander operates with REVAC. The consoles are expandable up to 128 zones with multiplication of 16 zones. These consoles are user-friendly systems with options for zone selection for individual zone announcement and common announcement through microphones.

## Features

- \* 24VDC Input voltage
- \* 19" Rack mountable.
- \* Power ON, Charger ON indications.
- \* RS-485 Communication with Indication.
- \* Membrane Keypad for user friendly operation.
- \* Zone Wise (Speaker line) Selection facility with LED indication.
- \* 100V audio output for Speaker.
- \* Plug Type Connector for easy wiring.
- \* Alarm activated on automatically announcing mode.
- \* Zones expansion in Multiple of 16.



## Specification

Input Voltage	: 24VDC
Operating Temperature	: 0 - 49° C/32-120° F.
Relative Humidity	: 93 ± 2% RH (non-condensing) at 32 ±2° C/90 ±3° F.
audio output	: 100V
Max Wattage	: 400W / 16Z
Zone Output	: 25W per Zone
Audio Input	: From Main Console
Communication Interface	: RS-485
Dimensions(2U)	: (484 W X 88 H X 325D )mm

## Connection Diagram



## Ordering Information

Models	Description
RE-032XP	17-32 Zone PA Expander
RE-048XP	33-48 Zone PA Expander
RE-064XP	49-64 Zone PA Expander
RE-080XP	65-80 Zone PA Expander
RE-096XP	81-96 Zone PA Expander
RE-112XP	97-112 Zone PA Expander
RE-128XP	113-128 Zone PA Expander

## Compatible Devices:

MODEL	DESCRIPTION
REVAC	PA Console
RE-LS10W	PA Wall Speaker
RE-LS10C	PA Ceiling Speaker

### India:

**RAVEL ELECTRONICS PVT LTD.,**  
 (An ISO 9001 Certified Company)  
 150A, Electronics Industrial Estate, Perungudi, Chennai - 96 .India.  
 E-Mail: [marketing@ravelfire.com](mailto:marketing@ravelfire.com); Web : [www.ravelfire.com](http://www.ravelfire.com)

### United Kingdom:

**RAVEL ELECTRONICS LTD.,**  
 Unit 11, Chancel Industrial Estate, Newhall street,  
 Willenhall WV13 1NX, West Midlands, United Kingdom.  
 E-mail: [info@ravelfire.co.uk](mailto:info@ravelfire.co.uk); Web: [www.ravelfire.co.uk](http://www.ravelfire.co.uk)