

# RE-737M

## Analogue Addressable Manual Call Point



### Product Overview:

The RE-737M Manual Call Point complies with latest standards and is designed to interface with addressable fire alarm panel. The RED blinking LED indicates normal operating condition.

Activation of MCP is indicated by RED steady LED.

### Features:

- Complies EN54-11.
- Type “A” Indoor Use
- Resettable by an element kit.
- Suitable for flush or surface mounting
- Inbuilt - Isolator
- Soft Addressing using programming tool.
- Low Standby Current.



### Electrical Specification

Operating Voltage	: 24VDC.
Quiescent Current	: 0.5mA.
Alarm Current	: 2.5mA.
Operating Temperature	: 0°C to 49°C.
Relative Humidity	: 0 - 93% non-condensing.
Storage temp	: 0°C to 60°C.


### Mechanical Characteristics

Connection	: 2.5mm <sup>2</sup> Max.
Weight	: 125g.
IP Rating	: IP 50.
Dimension	: 86mm X 86mm X 50mm.

### Ordering Information:

Model	Description
RE-737M	Analogue Addressable Manual Call Point

### Wiring Diagram



Note:-

Input & Output + / - are sensitive, be ensure that wiring before power up.

#### India:

**RAVEL ELECTRONICS PVT LTD.,**  
(An ISO 9001 Company)  
150A, Electronics Industrial Estate, Perungudi, Chennai - 96 .India.  
E-Mail: marketing@ravelfire.com; Web : www.ravelfire.com

#### United Kingdom:

**RAVEL ELECTRONICS LTD.,**  
Unit 11, Chancel Industrial Estate, Newhall street,  
Willenhall WV13 1NX, West Midlands, United Kingdom.  
E-mail: info@ravelfire.co.uk ;Web: www.ravelfire.co.uk